

MULTI-COLOR LED OPERATING MANUAL

These instructions are applicable to Vivid 360 Nicheless LED Multi-Color Lights programmed to be compatible with Pentair Controllers.

Vivid 360 Nicheless Multi-Color LED Pool Lights (P-Series) can be operated from either a wall switch or connected up to a Pentair Controller.

When connected to the Pentair IntelliTouch® or EasyTouch® Controller, the fixed colors and color-shows can be easily selected using the controller.

When connected to a Wall Switch, manually switching on and off a specific number of times activates the fixed color modes and color-shows.

Lights will always start up in the previously selected color. To change from this setting, turn the wall switch off/on a specific number of times (as shown below) until your desired color or color-show is reached.

During the off/on switching process, the light is turned off for a short period until the selected color is displayed. During this time, the pool will not be illuminated.

PROGRAMMING MODES			
	CYCLES	MODE	MODE DESCRIPTION
Number of times to cycle power (1-14)	1	SAm®	Cycles through white, magenta, blue and green colors (emulates the Pentair SAm® color changing light)
	2	Party	Rapid color changing building energy and excitement
	3	Romance	Slow color transitions creating a mesmerizing and calming effect
	4	Caribbean	Transitions between a variety of blues and greens
	5	American	Patriotic red, white and blue transition
	6	California Sunset	Dramatic transitions of orange, red and magenta tones
	7	Royal	Richer, deeper color tones
	8	Blue	Fixed color
	9	Green	Fixed color
	10	Red	Fixed color
	11	White	Fixed color
	12	Magenta	Fixed color
	13	Hold	Save the current color effect during a color light show
	14	Recall	Activate the last saved color effect.

Example: To select **California Sunset Mode**; turn the light on, then turn off and on six times. During the off/on switching process, no illumination will occur.

Vivid 360 Nicheless Operating Voltage: 12v AC **Vivid 360 Nicheless Power Consumption:** 16 watts max.

For supply connection, use only an isolating low voltage power supply with ungrounded output, evaluated for swimming pool use.

WARNING

Never stare directly at LED Pool Lights. Prolonged direct exposure can cause eye damage.

All Pentair trademarks are owned by Pentair, Inc. EasyTouch®, SAm® and IntelliTouch® are registered trademarks of Pentair Water Pool and Spa, Inc. and/or its affiliated companies in the USA and/or other countries.